

## 1. Hard Drives

Classify the compatible HDD into three types, enterprise, video surveillance and desktop. We recommend user to choose enterprise-level HDD and video surveillance-level HDD, which are with better command timeout control and reliability.

For the following conditions, we only suggest using enterprise-level HDD:

1. When the number of HDD is more than, or equal to, 5 HDDs.
2. When the NVR is installed on rack.

Green series hard drives should never be used with NUUO recorders to avoid data lost due to long wake up time from a sleeping drive.

### [3.5-inch Hard Drives] Video Surveillance

Vendor	Family	Model	Capacity	Interface	FW	Tested Model	
						Solo Plus 2 bay	Solo Plus 8 bay
Seagate	Surveillance	ST6000VX0001	6TB	SATA 6Gb/s	VN02		V
		ST4000VX000	4TB	SATA 6Gb/s	CV13		V
	SkyHawk	ST14000VX0008	14TB	SATA 6Gb/s	AV01	V	V
		ST10000VX0004	10TB	SATA 6Gb/s	AV01		V
		ST8000VX004	8TB	SATA 6Gb/s	AV01	V	
		ST6000VX001	6TB	SATA 6Gb/s	CV11		V
		ST8000VX022	8TB	SATA 6Gb/s	AV01		V
		ST4000VX005_SMR	4TB	SATA 6Gb/s	CV10	V	
	SkyHawk AI	ST18000VE000	18TB	SATA 6Gb/s	EV01	V	V
		ST18000VE002	18TB	SATA 6Gb/s	EV01	V	V
		ST16000VE002	16TB	SATA 6Gb/s	EV01	V	V
		ST12000VE001	12TB	SATA 6Gb/s	EV01	V	V
		ST10000VE004	10TB	SATA 6Gb/s	EV01	V	V
		ST10000VE001	10TB	SATA 6Gb/s	EV01	V	V
		ST10000VE000	10TB	SATA 6Gb/s	EV01	V	V
		ST8000VE001	8TB	SATA 6Gb/s	EV01	V	V
	ST8000VE000	8TB	SATA 6Gb/s	EV01	V	V	
	WD	Purple Series	WD101PURZ	10TB	SATA 6Gb/s		V
WD60PURX			6TB	SATA 6Gb/s	0A80		V
WD40PURX			4TB	SATA 6Gb/s	80		V

Some listed devices may not be available, please check with your local vendors.

\*Newly tested compatible hard drive models

## [2.5-inch Hard Drives] For 1bay device only Enterprise

Vendor	Family	Model	Capacity	Interface	Firmware
WD	WD AV-25	WD 10JUCT	1TB	SATA 3Gb/s	01.0
		WD5000LUCT	500GB	SATA 3Gb/s	01.0

Some listed devices may not be available, please check with your local vendors.

## 2. Monitor Support

Output Source	Resolution
HDMI VGA	1024x768, 60Hz
	1280x720, 60Hz
	1280x1024, 60Hz
	1920x1080, 60Hz
	2560x1440, 60Hz
	3840x2160, 60Hz

We improve HDMI compatibility in FW v1.1.2.

- 1) HDMI cable should be HDMI certificated, and its signal transmission quality depends on the diameter of wire (AWG) and the length of cable. If the length of your HDMI/VGA cable is over 1M, add a "repeater" to strengthen the signal.
- 2) When the UI/video image isn't at the correct location, correct it by the "auto adjust" function on the monitor or adjust it manually.
- 3) If encountering display issue, please use remote control to press the "10+" button, release it and press the "." button to switch monitor resolution (switching sequence: auto (default) → 1024x768 → 1280x720 → 1280x1024 → 1920x1080 → 3840x2160(Only NVRsolo Plus support)). If it fails, please check the signal out via PC to make sure monitor is under standard regulations.

## 3. Touch Panel Support

Vendor	Model
Acer	T232HL
ViewSonic	TD2220

## 4. UPS Support

Vendor	Model
APC	APC Smart-UPS XL 3000VA (SUA3000XL)
APC	APC Back-UPS ES 500VA (BE500TW)

## 5. DAS Support

Vendor	Model	Host Interface	HDD
Promise	SmartStor DS4600	eSATA	SATA

## 6. UPnP Router (auto port-forwarding)

Vendor	Model
D-Link	DIR-300

**Note:** This is the model we tested for auto port-forwarding function. Basically, all router possess UPnP function should be compatible.

## 7. Joystick Support

Vendor	Model
Axis	T8311
Axis	295
Logitech	Attack 3

**Note:** NUUO supports all the models of joysticks that are compatible with Windows.

## Supported functions:

Type	Function
<b>View &amp; Camera</b>	Goto View # Goto Previous Camera Goto Next Camera
<b>Screen Layout Switch</b>	Switch Screen Layout Toggle Single Camera View Toggle Full Screen
<b>PTZ Control</b>	Goto Preset Point # Zoom Out Zoom In Start/Stop Patrol

## Web Browser

Web	Internet Explorer 8 (32 bit)					
<b>OS</b>	Windows XP-SP3 32 bit	Windows 2003-SP2	Windows Vista-SP2	Windows 7 32/64 bit	Windows 8 32/64 bit	Windows 10 32/64 bit
<b>PASS/FAIL</b>	PASS	X	X	PASS	-	-
Web	Internet Explorer 9 (32 bit)					
<b>OS</b>	Windows XP-SP3 32 bit	Windows 2003-SP2	Windows Vista-SP2	Windows 7 32/64 bit	Windows 8 32/64 bit	Windows 10 32/64 bit
<b>PASS/FAIL</b>	-	X	X	PASS	-	-
Web	Internet Explorer 10 (32 bit)					
<b>OS</b>	Windows XP-SP3 32 bit	Windows 2003-SP2	Windows Vista-SP2	Windows 7 32/64 bit	Windows 8 32/64 bit	Windows 10 32/64 bit
<b>PASS/FAIL</b>	-	-	-	PASS	PASS	-
Web	Internet Explorer 11					
<b>OS</b>	Windows XP-SP3 32 bit	Windows 2003-SP2	Windows Vista-SP2	Windows 7 32/64 bit	Windows 8/8.1 32/64 bit	Windows 10 32/64 bit
<b>PASS/FAIL</b>	-	-	-	PASS	PASS	Pass
Web	Chrome*					
<b>OS</b>	Windows XP-SP3 32 bit	Windows 2003-SP2	Windows Vista-SP2	Windows 7 64 bit	Windows 8 64 bit	Windows 10 64 bit
<b>PASS/FAIL</b>	-	-	-	PASS	PASS	Pass
Web	Safari v6.1*					
<b>OS</b>	MAC OS X 10.6	MAC OS X 10.7	MAC OS X 10.8	-	-	-
<b>PASS/FAIL</b>	-	PASS	PASS	-	-	-
Web	Safari v7.0*					
<b>OS</b>	MAC OS X 10.6	MAC OS X 10.7	MAC OS X 10.8	-	-	-
<b>PASS/FAIL</b>	-	PASS	PASS	-	-	-

-: not available

X: not compatible

\*Below functions are not supported on Safari or Chrome.

- POS
- Fisheye dewarp

## 9.ezNUUO

ezNUUO is supported on Windows Internet Explorer and Windows Chrome only. It is not supported on Mac Safari.

## 10.FTP

OS	Windows XP-SP3 32 bit	Windows 2003-SP2	Windows Vista-SP2	Windows 7 32/64 bit	Windows 8 32/64 bit
<b>PASS/FAIL</b>	PASS	X	X	PASS	PASS

X: not compatible

## 11.Remote Client

Remote PC System Requirements

<b>Remote PC Minimum Requirements</b>	
<b>OS Supported</b>	Windows XP 32 bit, Windows 7 32/64 bit, Windows 8 32/64 bit, Win10 32/64-bit
<b>CPU</b>	Intel Core 2 Duo, 2.6GHz
<b>RAM</b>	1GB
<b>User Interface</b>	HTTP Web browser - Internet Explorer 8, 9, 10,11 (32 bit) NUUO client application program